



LMR BATTERY SPECIFICATIONS	PART NUMBER
	BP8299MHUC

COMPATIBLE RADIOS	Motorola XTS3000, XTS3500, XTS5000
REPLACES OEM BATTERY	RNN4006B (3500 mAh)
COMPATIBLE CHARGERS	Endura TWC1-MT13B, TWC1M-MT13B, TWC2M-MT13-D, TWC6M-MT13B, TWC12M-MT13-D / Logic LEVCA-MT13MH
VOLTAGE	7.5V
CAPACITY	3800 mAh
CHEMISTRY	NiMH
CELL TYPE	Panasonic BK380A or equivalent
CHARGE CYCLES	500
CHARGE TYPE	Rapid or trickle
CONDITIONER COMPATIBLE	Yes
THERMAL PROTECTION	Yes
HOUSING MATERIAL	ABS
HOUSING SEAL	Ultrasonic weld
METAL WELDING	Pure nickel tabs w/ spot welder
CLIP	Included
WARRANTY	12 months
PRODUCT PHOTO	